

Internet telefon telepítési leírás

LINKSYS PAP2

- Csatlakoztatás a hálózathoz. (Az eszköz automatikus IP címkérésre van állítva)
- IP cím lekérdezése (dugjon egy hagyományos telefonkészüléket a csatlakozóba és nyomja meg: ****110#)
- Konfiguráló PC beállítása az eszköz IP cím tartományához.
- Internet Explorer böngésző indítása.
- A címsorba beírni az eszköz IP címét. (bemondott IP cím)
- A megjelenő ablakban nyomja az Admin Logon gombot.

SYSTEM menü: (Itt állítható be az automatikus vagy statikus IP cím.)

The screenshot displays the Linksys PAP2 web interface. At the top, the Linksys logo and 'A Division of Cisco Systems, Inc.' are visible on the left, and 'Firmware Version: 2.0.12(LS)' is on the right. The main header area includes 'Voice' on the left, 'Phone Adapter with 2 Ports for Voice-Over-IP' in the center, and 'PAP2' on the right. Below this, there are tabs for 'Info', 'System', 'SIP', 'Regional', 'Line 1', 'Line 2', 'User 1', and 'User 2'. The 'System' tab is selected, and the page is in 'Basic View' with a link to 'switch to advanced view' and a 'User Login' link.

The main content area is titled 'System Configuration' and is divided into three sections:

- Internet Connection Type:** Contains 'Enable Web Server' (set to 'yes'), 'DHCP' (set to 'yes'), 'Static IP', 'Gateway', and 'NetMask' (all empty text boxes).
- Optional Network Configuration:** Contains 'HostName', 'Primary DNS', 'DNS Query Mode' (set to 'Parallel'), 'Debug Server', 'Domain', 'Secondary DNS', 'Syslog Server', and 'Debug Level' (set to '0').

At the bottom of the configuration area, there are two buttons: 'Save Settings' and 'Cancel Settings'. The Cisco Systems logo is visible in the bottom right corner of the interface.

Beállítás után: Save Settings!

Line1 menü: (itt állítható be a telefonszám és a hangtömörítés)

The screenshot shows the Cisco SIP configuration interface for Line 1. The interface is divided into several sections:

- SIP Settings:** Line Enable: yes; SIP Port: 5060
- Proxy and Registration:** Proxy: sip.neophonex.hu; Register: yes; Make Call Without Reg: no; Register Expires: 3600; Ans Call Without Reg: no
- Subscriber Information:** Display Name: megjelenítendőnév; Password: jelszó; Auth ID: telefonszám; User ID: telefonszám; Use Auth ID: no
- Supplementary Service Subscription:** Call Waiting Serv: yes; Block ANC Serv: yes; Cfwd All Serv: yes; Cfwd No Ans Serv: yes; Cfwd Last Serv: yes; Accept Last Serv: yes; CID Serv: yes; Call Return Serv: yes; Three Way Call Serv: yes; Attn Transfer Serv: yes; MVM Serv: yes; Block CID Serv: yes; Dist Ring Serv: yes; Cfwd Busy Serv: yes; Cfwd Sel Serv: yes; Block Last Serv: yes; DND Serv: yes; CWCID Serv: yes; Call Back Serv: yes; Three Way Conf Serv: yes; Unattn Transfer Serv: yes; VMM Serv: yes
- Audio Configuration:** Preferred Codec: G723; Use Pref Codec Only: no; DTMF Tx Method: InBand; Silence Supp Enable: no; FAX CED Detect Enable: yes

Buttons: Save Settings, Cancel Settings

Beállítás után: Save Settings!

- Második telefonszám használata esetén a Line2 beállítása megegyezik az előzővel.
- Újraindítás.